SIEMENS

Data sheet

6AV6671-8XE00-0AX0

converter RS-422, male, 9-pole to RS-232 male, 9-pole, can be screwed together with RS-422 interface, cable outlet 180 degrees, for connection of third-party PLC, scope of supply: 1 converter



| General information | |
|---------------------------------------------------|-------------------------------------------------------------------|
| Product type designation | Converter, RS 422 to RS 232 |
| Installation type/mounting | |
| Wall mounting/direct mounting | Yes; Can be screwed onto the HMI |
| Interfaces | |
| HMI-side interface | |
| Number of pins HMI-side | 9; Male (RS 422) |
| Device-side interface | |
| Number of pins device-side | 9; Female (RS 232) |
| Degree and class of protection | |
| IP (all-round) | none |
| Standards, approvals, certificates | |
| CE mark | Yes |
| RoHS conformity | Yes |
| China RoHS compliance | Yes |
| Ambient conditions | |
| Ambient temperature during operation | |
| • min. | 0 °C |
| • max. | 55 °C |
| Ambient temperature during storage/transportation | |
| • min. | -20 °C |
| • max. | 70 °C |
| Relative humidity | |
| Operation, max. | 95 % |
| Mechanics/material | |
| Enclosure material (front) | |
| Plastic | Yes |
| Screw type | |
| • 4.5 V | Yes; HMI page |
| Torques/forces | |
| Tightening torque, min. | 0.18 N·m; Insufficient torque can lead to loosening of the screws |
| Tightening torque, max. | 0.2 N·m |
| Tightening torque, recommended | 0.2 N⋅m; Higher torques may damage the product |
| Dimensions | |
| Width | 31 mm |
| Height | 50 mm |
| Thickness | 11 mm |
| Weights | |
| Weight (without packaging) | 26 g |
| Scope of supply | |

| Delivery quantity in pieces | 1 |
|----------------------------------|--------------------------------------------------------------------------------------------------------------------------|
| Other | |
| Merchandise | No |
| Manufacturer name | SIEMENS AG |
| Manufacturer's address | Gleiwitzerstraße 555, 90475 Nuremberg, Germany |
| Target devices | suitable for all SIMATIC HMI RS 422 interfaces, for details refer to the operating instructions of the respective device |
| Usable in the following products | |
| Product 1 | 6AV6642-0* |
| Product 2 | 6AV6542-0* |
| • Product 3 | 6AV6545-0* |
| Product 4 | 6AV6644-* |
| Product 6 | 6AV6640-0C* |
| Product 7 | 6AV6643-7BA00-* |
| Product 8 | 6AV6643-7CD00-* |
| • Product 9 | 6AV6643-7DD00-* |
| • Product 10 | 6AV2124-* |
| Product 11 | 6AV2128-3* |
| • Product 13 | 6AV6647-* |
| Product 14 | 6AV6643-8* |
| Product 15 | 6AV2123-2* |

last modified:

5/22/2024