SIEMENS

Data sheet

6EP4437-7EB00-3CX0



SITOP SEL1400/4X2-10A

SITOP SEL1400 10 A selectivity module 4-channel with limiting characteristic input: 24 V DC/40 A output: 24 V DC/4x 10 A threshold adjustable 2-10 A with monitoring interface

input		
type of the power supply network	Controlled DC voltage	
supply voltage at DC rated value	24 V	
input voltage at DC	20.4 30 V	
overvoltage overload capability	35 V	
input current at rated input voltage 24 V rated value	40 A	
output		
voltage curve at output	controlled DC voltage	
formula for output voltage	Vin - approx. 0.2 V	
relative overall tolerance of the voltage note	In accordance with the supplying input voltage	
number of outputs	4	
output current up to 60 °C per output rated value	10 A; +60 +70 °C: Derating 2%/K	
Adjustable output current	2 10 A	
type of response value setting	via potentiometer	
response delay maximum	5 s; with load-optimized switch-on of all 4 channels	
product feature parallel switching of outputs	Yes	
type of outputs connection	Connection of all outputs after ramp-up of the supply voltage > 20 V; delay time of 25 ms, 200 ms, 500 ms or "load-optimized" can be set via DIP switch for sequential connection	
power loss		
efficiency in percent	98 %	
power loss [W] at rated output voltage for rated value of the output current typical	10 W	
switch-off characteristic		
switching characteristic		
 of the excess current 	lout = 1.01.5 x set value, switch-off after approx. 5 s	
 of the current limitation 	lout = 1.5 x set value, switch-off after typ. 100 ms	
 of the immediate switch-off 	lout > set value and Vin < 20 V, switch-off after approx. 0.5 ms	
design of the reset device/resetting mechanism	via sensor per output	
remote reset function	Non-electrically isolated 24 V input (signal level "high" at > 15 V)	
protection and monitoring		
fuse protection type at input	15 A per output (not accessible)	
display version for normal operation	Three-color LED per output: green LED for "Output switched through"; yellow LED for "Output switched off manually"; red LED for "Output switched off due to overcurrent"	
design of the switching contact for signaling function	Floating common signal contact or status signal output (pulse/pause signal that can be evaluated via SIMATIC function block)	
safety		
galvanic isolation between input and output at switch-off	No	
standard for safety	according to EN 60950-1 and EN 50178	
operating resource protection class	Class III	
protection class IP	IP20	

standard		
 for emitted interference 	EN 61000-6-3	
 for interference immunity 	EN 61000-6-2	
standards, specifications, approvals		
certificate of suitability		
CE marking	Yes	
UL approval	Yes; UL-Recognized (UL 2367) File E328600; cULus-Listed (UL 508, CSA	
	C22.2 No. 107.1) File E197259	
CSA approval	Yes; CSA C22.2 60950-1	
EAC approval	Yes	
type of certification	V	
CB-certificate	Yes	
standards, specifications, approvals hazardous environments		
certificate of suitability	Al-	
IECEX ATEX	No No	
	NO	
standards, specifications, approvals marine classification	Ma	
shipbuilding approval	No	
standards, specifications, approvals Environmental Product De		
Environmental Product Declaration	Yes	
Global Warming Potential [CO2 eq]	565 kg	
• total	565 kg	
during manufacturingduring operation	32.5 kg	
after end of life	532 kg	
ambient conditions	0.52 kg	
ambient temperature	-40 +70 °C; with natural convection	
during operationduring transport	-40 +85 °C	
during transport during storage	-40 +85 °C	
environmental category according to IEC 60721	Climate class 3K3, 5 95% no condensation	
connection method	Olimate class site, 5 35 % no condensation	
	Push-in	
type of electrical connection	24\/1 24\/2: nush-in for 0.5 16 mm²: 0\/1 0\/2: nush-in for 0.5 4 mm²	
• at input	24V1, 24V2: push-in for 0.5 16 mm²; 0V1, 0V2: push-in for 0.5 4 mm²	
at input at output	Output 1 4: push-in for 0.5 4 mm ²	
at inputat outputfor auxiliary contacts	Output 1 4: push-in for 0.5 4 mm ² RST: push-in for 0.2 1.5 mm ²	
at inputat outputfor auxiliary contactsfor signaling contact	Output 1 4: push-in for 0.5 4 mm ²	
 at input at output for auxiliary contacts for signaling contact mechanical data	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm²	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm²	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm	
at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 × 225 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 × 225 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 x 225 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 × 225 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link to website: Industry Mall 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 × 225 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link to web page: selection aid TIA Selection Tool 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg https://mall.industry.siemens.com https://www.siemens.com/tstcloud	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link to website: Industry Mall to website: Industrial communication to website: CAx-Download-Manager to website: Industry Online Support 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 × 225 mm 45 mm 0 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg https://mall.industry.siemens.com https://www.siemens.com/tstcloud https://siemens.com/industrial-communication	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link to website: Industry Mall to website: Industrial communication to website: CAx-Download-Manager • to website: CAx-Download-Manager	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg https://mall.industry.siemens.com https://www.siemens.com/industrial-communication https://siemens.com/industrial-communication https://siemens.com/cax	
 at input at output for auxiliary contacts for signaling contact mechanical data width × height × depth of the enclosure installation width × mounting height required spacing top bottom left right fastening method standard rail mounting S7 rail mounting wall mounting housing can be lined up net weight further information internet links internet link to website: Industry Mall to website: Industrial communication to website: CAx-Download-Manager to website: Industry Online Support 	Output 1 4: push-in for 0.5 4 mm² RST: push-in for 0.2 1.5 mm² 13, 14: push-in for 0.2 1.5 mm² 45 × 135 × 125 mm 45 mm 45 mm 0 mm Snaps onto DIN rail EN 60715 35x7.5/15 Yes No No Yes 0.3 kg https://mall.industry.siemens.com https://www.siemens.com/industrial-communication https://siemens.com/industrial-communication https://siemens.com/cax	

security information

security information

Siemens provides products and solutions with industrial cybersecurity functions that support the secure operation of plants, systems, machines and networks. In order to protect plants, systems, machines and networks against cyber threats, it is necessary to implement – and continuously maintain – a holistic, state-of-the-art industrial cybersecurity concept. Siemens' products and solutions constitute one element of such a concept. Customers are responsible for preventing unauthorized access to their plants, systems, machines and networks. Such systems, machines and components should only be connected to an enterprise network or the internet if and to the extent such a connection is necessary and only when appropriate security measures (e.g. firewalls and/or network segmentation) are in place. For additional information on industrial cybersecurity measures that may be implemented, please visit www.siemens.com/cybersecurity-industry. Siemens' products and solutions undergo continuous development to make them more secure. Siemens strongly recommends that product updates are applied as soon as they are available and that the latest product versions are used. Use of product versions that are no longer supported, and failure to apply the latest updates may increase customer's exposure to cyber threats. To stay informed about product updates, subscribe to the Siemens Industrial Cybersecurity RSS Feed under https://www.siemens.com/cert. (V4.7)

Classifications

Version	Classification
14	27-37-18-02
12	27-37-18-02
9.1	27-37-18-02
9	27-37-18-02
8	27-37-18-02
7.1	27-37-18-02
6	27-37-18-02
9	EC001440
8	EC001440
7	EC001440
4	4727
15	39-12-15-21
	14 12 9.1 9 8 7.1 6 9 8 7

Approvals Certificates

General Product Approval



Manufacturer Declaration Declaration of Conformity







General Product Approval

Environment





last modified:

6/24/2024