SIEMENS

Data sheet

6ES7134-6GD01-2BA1



SIMATIC ET 200SP, ANALOG INPUT MODULE, AI 4XI 2-/4-WIRE STANDARD, PACKING UNIT: 10 PIECES, FITS TO BU-TYPE A0, A1, COLOR CODE CC03, MODULE DIAGNOSIS, 16BIT, +/-0,3%

General information	
Product type designation	Al 4xl 2-/4-wire ST
HW functional status	From FS02
Firmware version	
 FW update possible 	Yes
usable BaseUnits	BU type A0, A1
Color code for module-specific color identification plate	CC03
Product function	
● I&M data	Yes; I&M0 to I&M3
 Isochronous mode 	No
Measuring range scalable	No
Engineering with	
 STEP 7 TIA Portal configurable/integrated from version 	V14 / -
 STEP 7 configurable/integrated from version 	V5.6 and higher
 PCS 7 configurable/integrated from version 	V8.1 SP1
 PROFIBUS from GSD version/GSD revision 	One GSD file each, Revision 3 and 5 and higher
 PROFINET from GSD version/GSD revision 	GSDML V2.3
Operating mode	
 Oversampling 	No
• MSI	No
CiR - Configuration in RUN	
Reparameterization possible in RUN	Yes
Calibration possible in RUN	No
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
Reverse polarity protection	Yes
Input current	
Current consumption, max.	37 mA; without sensor supply
Encoder supply	
24 V encoder supply	
• 24 V	Yes
Short-circuit protection	Yes
Output current, max.	20 mA; max. 50 mA per channel for a duration < 10 s
Power loss	
Power loss, typ.	0.85 W; Without encoder supply voltage
Address area	
Address space per module	
 Address space per module, max. 	8 byte; + 1 byte for QI information

Hardware configuration	
Automatic encoding	Yes
Mechanical coding element	Yes
Type of mechanical coding element	Type A
Selection of BaseUnit for connection variants	1,500
2-wire connection	BU type A0, A1
4-wire connection	BU type A0, A1
Analog inputs	20 (ypo 7.0, 7.1
Number of analog inputs	4; Differential inputs
permissible input current for current input (destruction limit),	50 mA
Max.	Sum of the basic conversion times and additional processing times (depending
Cycle time (all channels), min.	Sum of the basic conversion times and additional processing times (depending on the parameterization of the active channels)
Input ranges (rated values), currents	
• 0 to 20 mA	Yes; 16 bit incl. sign
— Input resistance (0 to 20 mA)	100 Ω ; + approx. 0.7 V diode forward voltage in 2-wire operation
• -20 mA to +20 mA	Yes
— Input resistance (-20 mA to +20 mA)	100 Ω
• 4 mA to 20 mA	Yes; 15 bit
— Input resistance (4 mA to 20 mA)	100 Ω ; + approx. 0.7 V diode forward voltage in 2-wire operation
Cable length	
• shielded, max.	1 000 m
Analog value generation for the inputs	
Measurement principle	integrating (Sigma-Delta)
Integration and conversion time/resolution per channel	
Resolution with overrange (bit including sign), max.	16 bit
Integration time, parameterizable	Yes
 Interference voltage suppression for interference frequency f1 in Hz 	16.6 / 50 / 60 Hz
 Conversion time (per channel) 	180 / 60 / 50 ms
Smoothing of measured values	
 Number of smoothing levels 	4; None; 4/8/16 times
 parameterizable 	Yes
parameterizable Encoder	Yes
	Yes
Encoder	Yes No
Encoder Connection of signal encoders	
Encoder Connection of signal encoders • for voltage measurement	No
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer	No Yes
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max.	No Yes 650 Ω
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer	No Yes 650 Ω
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies	No Yes 650 Ω Yes
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-)	No Yes 650 Ω Yes
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input	No Yes 650 Ω Yes 0.01 % 0.005 %/K
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-)	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 %
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-)	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 %
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C)	No Yes $650~\Omega$ Yes $0.01~\%$ $0.005~\%/K$ $50~dB;~Applies~to~up~to~\pm5~V~overvoltage~in~other~channels$ $0.05~\%$ $0.5~\%$
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the following suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the following suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the following suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the following suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the following suppression for f = n x (f1 +/- 1 %), f1 = interference solves as a constant of the first of t	No Yes $650~\Omega$ Yes $0.01~\%$ $0.005~\%/K$ $50~dB;~Applies~to~up~to~\pm5~V~overvoltage~in~other~channels$ $0.05~\%$ $0.5~\%$
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference value of interference < rated value of input range), min.	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for fer not the formula of input range), min. • Common mode voltage, max.	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB 10 V
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference value of interference (peak value of interference < rated value of input range), min. • Common mode voltage, max. • Common mode interference, min.	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.4 % 0.5 % 1.5 %
Encoder Connection of signal encoders • for voltage measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB 10 V
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interested value of input range), min. • Series mode interference (peak value of interference < rated value of input range), min. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function Alarms	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.3 % rference frequency 70 dB 10 V 90 dB Yes
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB 10 V 90 dB Yes Yes
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Limit value alarm	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.3 % rference frequency 70 dB 10 V 90 dB Yes
Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Limit value alarm Diagnoses	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB 10 V 90 dB Yes Yes No
Encoder Connection of signal encoders • for voltage measurement • for current measurement as 2-wire transducer — Burden of 2-wire transmitter, max. • for current measurement as 4-wire transducer Errors/accuracies Linearity error (relative to input range), (+/-) Temperature error (relative to input range), (+/-) Crosstalk between the inputs, min. Repeat accuracy in steady state at 25 °C (relative to input range), (+/-) Operational error limit in overall temperature range • Current, relative to input range, (+/-) Basic error limit (operational limit at 25 °C) • Current, relative to input range, (+/-) Interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage suppression for f = n x (f1 +/- 1 %), f1 = interference voltage, max. • Common mode voltage, max. • Common mode interference, min. Interrupts/diagnostics/status information Diagnostics function Alarms • Diagnostic alarm • Limit value alarm	No Yes 650 Ω Yes 0.01 % 0.005 %/K 50 dB; Applies to up to ±5 V overvoltage in other channels 0.05 % 0.5 % 0.3 % rference frequency 70 dB 10 V 90 dB Yes Yes

Short-circuit	Yes; 2-wire mode: Short-circuit of the encoder supply to ground or of an input to the encoder supply
Group error	Yes
 Overflow/underflow 	Yes
Diagnostics indication LED	
 Monitoring of the supply voltage (PWR-LED) 	Yes; green LED
 Channel status display 	Yes; green LED
 for channel diagnostics 	No
 for module diagnostics 	Yes; green/red LED
Potential separation	
Potential separation channels	
• between the channels	Yes; channel group-specific between 2-wire current input group and 4-wire voltage input group
 between the channels and backplane bus 	Yes
 between the channels and the power supply of the electronics 	Yes; only for 4-wire transducer
Permissible potential difference	
between the inputs (UCM)	10 V DC
Isolation	
Isolation tested with	707 V DC (type test)
Ambient conditions	
Ambient temperature during operation	
 horizontal installation, min. 	-30 °C; < 0 °C as of FS02
 horizontal installation, max. 	60 °C
 vertical installation, min. 	-30 °C; < 0 °C as of FS02
 vertical installation, max. 	50 °C
Altitude during operation relating to sea level	
 Installation altitude above sea level, max. 	5 000 m; Restrictions for installation altitudes > 2 000 m, see manual
Dimensions	
Width	15 mm
Height	73 mm
Depth	58 mm
Weights	
Weight, approx.	31 g

last modified: 5/22/2024 🖸